

# Signal Processing First

## Lecture 8 Sampling & Aliasing

8/22/2003

© 2003, JH McClellan & RW Schaffer

1

## READING ASSIGNMENTS

- This Lecture:
  - Chap 4, Sections 4-1 and 4-2
    - Replaces Ch 4 in DSP First, pp. 83-94
- Other Reading:
  - Recitation: Strobe Demo (Sect 4-3)
  - Next Lecture: Chap. 4 Sects. 4-4 and 4-5

8/22/2003


© 2003, JH McClellan & RW Schaffer

3

## LECTURE OBJECTIVES

- SAMPLING can cause ALIASING
  - Sampling Theorem
  - Sampling Rate > 2(Highest Frequency)
- Spectrum for digital signals,  $x[n]$ 
  - Normalized Frequency

$$\hat{\omega} = \omega T_s = \frac{2\pi f}{f_s} + 2\pi \ell$$

 **ALIASING**

8/22/2003

© 2003, JH McClellan & RW Schaffer

4

## SYSTEMS Process Signals



- PROCESSING GOALS:
  - Change  $x(t)$  into  $y(t)$ 
    - For example, more BASS
  - Improve  $x(t)$ , e.g., image deblurring
  - Extract Information from  $x(t)$

8/22/2003

© 2003, JH McClellan & RW Schaffer

5

# System IMPLEMENTATION

## ANALOG/ELECTRONIC:

- Circuits: resistors, capacitors, op-amps



## DIGITAL/MICROPROCESSOR

- Convert  $x(t)$  to **numbers** stored in memory



8/22/2003

© 2003, JH McClellan & RW Schaffer

6


# SAMPLING $x(t)$

## SAMPLING PROCESS

- Convert  $x(t)$  to **numbers**  $x[n]$
- " $n$ " is an integer;  $x[n]$  is a sequence of values
- Think of " $n$ " as the storage address in memory

## UNIFORM SAMPLING at $t = nT_s$

- IDEAL:  $x[n] = x(nT_s)$



8/22/2003


© 2003, JH McClellan & RW Schaffer

7

# SAMPLING RATE, $f_s$

## SAMPLING RATE ( $f_s$ )




- $f_s = 1/T_s$ 
  - NUMBER of SAMPLES PER SECOND
- $T_s = 125 \text{ microsec} \rightarrow f_s = 8000 \text{ samples/sec}$ 
  - UNITS ARE HERTZ: 8000 Hz
- UNIFORM SAMPLING at  $t = nT_s = n/f_s$ 
  - IDEAL:  $x[n] = x(nT_s) = x(n/f_s)$



8/22/2003

© 2003, JH McClellan & RW Schaffer

8



8/22/2003

9

# SAMPLING THEOREM


- HOW OFTEN ?
  - DEPENDS on FREQUENCY of SINUSOID
  - ANSWERED by SHANNON/NYQUIST Theorem
  - ALSO DEPENDS on "**RECONSTRUCTION**"

## Shannon Sampling Theorem

A continuous-time signal  $x(t)$  with frequencies no higher than  $f_{\max}$  can be reconstructed exactly from its samples  $x[n] = x(nT_s)$ , if the samples are taken at a rate  $f_s = 1/T_s$  that is greater than  $2f_{\max}$ .

# Reconstruction? Which One?

Given the samples, draw a sinusoid through the values



$$x[n] = \cos(0.4\pi n)$$

When  $n$  is an integer  
 $\cos(0.4\pi n) = \cos(2.4\pi n)$

# STORING DIGITAL SOUND

- $x[n]$  is a SAMPLED SINUSOID
  - A list of numbers stored in memory
- EXAMPLE: audio CD
- CD rate is 44,100 samples per second
  - 16-bit samples
  - Stereo uses 2 channels
- Number of bytes for 1 minute is
  - $2 \times (16/8) \times 60 \times 44100 = 10.584$  Mbytes

# DISCRETE-TIME SINUSOID

- Change  $x(t)$  into  $x[n]$  **DERIVATION**

$$x(t) = A \cos(\omega t + \phi)$$

$$x[n] = x(nT_s) = A \cos(\omega nT_s + \phi)$$

$$x[n] = A \cos((\omega T_s)n + \phi)$$

$$x[n] = A \cos(\hat{\omega}n + \phi)$$

$$\hat{\omega} = \omega T_s = \frac{\omega}{f_s}$$

DEFINE DIGITAL FREQUENCY

## DIGITAL FREQUENCY $\hat{\omega}$

- $\hat{\omega}$  VARIES from 0 to  $2\pi$ , as  $f$  varies from 0 to the sampling frequency
- UNITS are radians, not rad/sec
  - DIGITAL FREQUENCY is NORMALIZED

$$\hat{\omega} = \omega T_s = \frac{2\pi f}{f_s}$$

8/22/2003

© 2003, JH McClellan & RW Schafer

14

## SPECTRUM (DIGITAL)

$$\hat{\omega} = 2\pi \frac{f}{f_s}$$

$$f_s = 1 \text{ kHz}$$

$$\frac{1}{2} X^*$$

$-0.2\pi$


$$\frac{1}{2} X$$

$2\pi(0.1)$

$$\hat{\omega}$$

$$x[n] = A \cos(2\pi(100)(n/1000) + \phi)$$

100-Hz Cosine Wave: Sampled with  $T_s = 1$  msec (1000 Hz)



## SPECTRUM (DIGITAL) ???

$$\hat{\omega} = 2\pi \frac{f}{f_s}$$

$$f_s = 100 \text{ Hz}$$

$$\frac{1}{2} X^*$$

$-2\pi$


$$\frac{1}{2} X$$

$2\pi(1)$

$$\hat{\omega}$$

$$x[n] = A \cos(2\pi(100)(n/100) + \phi)$$

100-Hz Cosine Wave: Sampled with  $T_s = 10$  msec (100 Hz)



## The REST of the STORY

- Spectrum of  $x[n]$  has more than one line for each complex exponential
  - Called ALIASING
  - MANY SPECTRAL LINES
- SPECTRUM is PERIODIC with period =  $2\pi$ 
  - Because

$$A \cos(\hat{\omega}n + \phi) = A \cos((\hat{\omega} + 2\pi)n + \phi)$$

8/22/2003

© 2003, JH McClellan & RW Schafer

17

## ALIASING DERIVATION

- Other Frequencies give the same  $\hat{\omega}$

$$x_1(t) = \cos(400\pi t) \quad \text{sampled at } f_s = 1000 \text{ Hz}$$

$$x_1[n] = \cos(400\pi \frac{n}{1000}) = \cos(0.4\pi n)$$

$$x_2(t) = \cos(2400\pi t) \quad \text{sampled at } f_s = 1000 \text{ Hz}$$

$$x_2[n] = \cos(2400\pi \frac{n}{1000}) = \cos(2.4\pi n)$$

$$x_2[n] = \cos(2.4\pi n) = \cos(0.4\pi n + 2\pi n) = \cos(0.4\pi n)$$

$$\Rightarrow x_2[n] = x_1[n] \quad 2400\pi - 400\pi = 2\pi(1000)$$

8/22/2003

© 2003, JH McClellan & RW Schaffer

18

## ALIASING DERIVATION-2

- Other Frequencies give the same  $\hat{\omega}$

$$\text{If } x(t) = A \cos(2\pi(f + \ell f_s)t + \varphi)$$

$$t \leftarrow \frac{n}{f_s}$$

$$\text{and we want: } x[n] = A \cos(\hat{\omega}n + \varphi)$$

$$\text{then: } \hat{\omega} = \frac{2\pi(f + \ell f_s)}{f_s} = \frac{2\pi f}{f_s} + \frac{2\pi \ell f_s}{f_s}$$

$$\hat{\omega} = \omega T_s = \frac{2\pi f}{f_s} + 2\pi \ell$$

8/22/2003

19

## ALIASING CONCLUSIONS

- ADDING  $f_s$  or  $2f_s$  or  $-f_s$  to the FREQ of  $x(t)$  gives exactly the same  $x[n]$ 
  - The samples,  $x[n] = x(n/f_s)$  are EXACTLY THE SAME VALUES
- GIVEN  $x[n]$ , WE CAN'T DISTINGUISH  $f_0$  FROM  $(f_0 + f_s)$  or  $(f_0 + 2f_s)$

8/22/2003

© 2003, JH McClellan & RW Schaffer

20

## NORMALIZED FREQUENCY

- DIGITAL FREQUENCY

*Normalized Radian Frequency*

$$\hat{\omega} = \omega T_s = \frac{2\pi f}{f_s} + 2\pi \ell$$

*Normalized Cyclic Frequency*

$$\hat{f} = \hat{\omega}/(2\pi) = f T_s = f/f_s$$

8/22/2003

© 2003, JH McClellan & RW Schaffer

21

## SPECTRUM for $x[n]$


- PLOT versus NORMALIZED FREQUENCY
- INCLUDE ALL SPECTRUM LINES
  - ALIASES
    - ADD MULTIPLES of  $2\pi$
    - SUBTRACT MULTIPLES of  $2\pi$
  - FOLDED ALIASES
    - (to be discussed later)
    - ALIASES of NEGATIVE FREQS

8/22/2003


© 2003, JH McClellan & RW Schaefer

22


## SPECTRUM (MORE LINES)




## SPECTRUM (ALIASING CASE)



## SAMPLING GUI (con2dis)



# SPECTRUM (FOLDING CASE)



$$x[n] = A \cos(2\pi(100)(n/125) + \varphi)$$

100-Hz Cosine Wave: Sampled with  $T_s = 8$  msec (125 Hz)

